



IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Volume: 9 Issue: VI Month of publication: June 2021

DOI: https://doi.org/10.22214/ijraset.2021.35313

www.ijraset.com

Call: 🕥 08813907089 🔰 E-mail ID: ijraset@gmail.com

CPWG Fed with Octagonal Patch Antenna

Dr. K. Ramesh Babu¹, Mr. Mesay Mengstie², Mr. Mulushewa Getachew³ ^{1, 2, 3}ECT Department, Ethiopian Technical University

Abstract: A Co planner Wave Guide (CPWG) fed with octagonal patch antenna is modified from their respective rectangular patch are presented for WLAN application. The dielectric material applied in the design process for both co planar and micro strip patch antenna is FR4 Epoxy Glass, which has relative permittivity of 4.4 and substrate height 1.6mm. Antenna parameters used to check the performance. A comparison is made between the octagonal co-planar antenna and octagonal micro strip antenna available. Ansys HFSS is used for antenna design and analysis. Both designed antennas are suitable for wireless local area network application and the design parameters of the antenna are optimized to resonate at 3GHz frequencies for WLAN applications. It has been found that octagonal micro strip patch antennas have lower return loss and are more directive than co planar patch antenna. High directivity of octagonal micro strip antenna is due to the presence of ground plane under the substrate of antenna. The results obtained by simulations have also shown that octagonal co planar patch antennas have high radiation efficiency (a measure of the power radiated through the antenna as an electromagnetic wave to the power fed to the antenna terminals) and which implies a wider bandwidth as compared to an octagonal micro strip patch antennas. The radiation efficiency obtained for micro strip patch antenna is 3.75 dB and that for a co-planar patch antenna is 3.75 dB. Kowwordy Co planar patch.

Keywords: Co-planar patch, CPWG, octagonal patch, planar etc.

I. INTRODUCTION

Planar patch antennas [20] are popular in wireless communication, because they have some advantages due to their conformal and simple planar structure. They allow all the advantages of printed -circuit technology. There are varieties of patch structures available but the rectangular, circular and triangular shapes [20] are most frequently used. Design of S-band (WIMAX), C-band (WLAN) antennas also got popularity with the advancement of planar patch antennas.

Moreover, a large number of co planar and micro strip patches to be used in wireless applications have been developed [21]. The rapid progress in wireless communications requires the development of lightweight, low profile, single feed antennas. Also it is highly desirable to integrate several RF modules for different frequencies into one piece of equipment. Hence, multiband antennas that can be used simultaneously in different standards have been in the focus points of many research projects [21]. Portable devices are widely used in our daily lives such as mobile phones, laptops with wireless connection.

The S-band is a certain portion of the microwave band of the electromagnetic spectrum. It is defined by an IEEE standard for radio waves with frequencies that range from 2 to 4 GHz, crossing the conventional boundary between UHF and SHF at 3.0 GHz. The S band is used by weather radar, and surface ship radar.

A certain portions of the electromagnetic spectrum, including wavelengths of microwave that are used for long distance telecommunications is called C-band. It ranges from 4 to 8 GHz and its slight variations contain frequency ranges that are used for, some Wi-Fi devices, some cordless telephones, and some weather radar systems.

The main goal of this work is to design a octagonal co planar and micro strip patch antennas which will be applicable for WLAN applications and do a performance comparison between these two planar patch antennas and put the most suitable antenna forward for Microwave application systems.

a large number of co-planar and micro strip patches to be used in wireless applications have been developed [21]. The rapid progress in wireless communications requires the development of lightweight, low profile, single feed antennas. Also it is highly desirable to integrate several RF modules for different frequencies into one piece of equipment. Hence, multi band antennas that can be used simultaneously in different standards have been in the focus points of many research projects [21]. Portable devices are widely used in our daily lives such as mobile phones, laptops with wireless connection. The S-band is a certain portion of the microwave band of the electromagnetic spectrum. It is defined by an IEEE standard for radio waves with frequencies that range from 2 to 4 GHz, crossing the conventional boundary between UHF and SHF at 3.0 GHz. The S band is used by weather radar, and surface ship radar. A certain portions of the electromagnetic spectrum, including wavelengths of microwave that are used for long distance telecommunications is called C-band. It ranges from 4 to 8 GHz and its slight variations contain frequency ranges that are used for, some Wi-Fi devices, some cordless telephones, and some weather radar systems.



International Journal for Research in Applied Science & Engineering Technology (IJRASET) ISSN: 2321-9653; IC Value: 45.98; SJ Impact Factor: 7.429 Volume 9 Issue VI Jun 2021- Available at www.ijraset.com

The main goal of this work is to design a octagonal co planar and micro strip patch antennas which will be applicable for WLAN applications and do a performance comparison between these two planar patch antennas and put the most suitable antenna forward for Microwave application systems.

A. Basic Structure of Micro Strip Patch Antenna

A class of antennas that has gained considerable popularity in recent years is the micro strip antenna. In its most fundamental form, a Micro strip Patch antenna consists of a radiating patch on one Side of a dielectric substrate which has aground plane on the other side as shown in Figure 2.1. The patch is generally made of conducting material such as copper or gold and can take any possible shape. The radiating patch and the feed lines are usually photo etched on the dielectric substrate. A typical micro strip element is illustrated in Fig. 2-1. There are many different types of micro strip antennas, but their common feature is that they consist of four parts:

- *1)* very thin flat metallic region often called the patch;
- 2) Dielectric substrate;
- 3) Ground plane, which is usually much larger than the patch; and
- 4) Feed, which supplies the element RF power.

Micro strip elements are often constructed by etching the patch (and sometimes the feeding circuitry) from a single printed-circuit board clad with conductor on both of its sides. In its simplest form, a micro strip patch antenna consists of a radiating patch on one side of a dielectric substrate, and a ground plane on the other side [22].



Figure 2.1: The basic geometry of micro strip radiator [33]

II. PREVIOUS WORK

To make parameter comparison, results found for both micro strip and co planar patch antenna are also included in the following table 2.1.

171	C 1 1 1		
Element	Calculated	Calculated	
	results	results	
	for co planar	for micro strip	
	patch	patch	
	antenna(mm)	antenna(mm)	
Width of patch	30.43	30.43	
(W)			
Length of patch	22.5	23.43	
(L)			
Width of ground	46	46	
(Wg)			
Length of ground	32	40	
(Lg)			
Inset length (Yo)	6.91	7.196	
Effective dielectric	4.49	4.08	
constant (Ereff)			



Volume 9 Issue VI Jun 2021- Available at www.ijraset.com

A. CPWG fed with Octagonal Patch Antenna

The next step is design of the octagonal patch microstrip and coplanar antenna, in this step we make a cut of a small triangular shape in the four angles of the microstrip patch antenna and coplanar patch as shown in Fig.2.1. select some value which gives wide band width and define the parameter which helps to find the rest four sides of the patch.this way it can obtain an octagonal patch antenna.

$$\mathbf{D} = (\mathbf{L}_{cut})\mathbf{2} + (\mathbf{w}_{cut})\mathbf{2}$$

Where D is the sides (cuts) from rectangular patch

$$L_{cut} \frac{Lp}{C} = W_{cut} = \frac{Lp}{C}$$
, wp width of rectangular patch, Lp length of rectangular patch,



Figure 2.1: octagonal patch micro strip antenna

B. Antenna Parameters

1) Efficiency and Quality Factor: For a microstrip patch antenna, efficiency can be defined as the power radiated from the microstrip element divided by the power received by the input to the element. Factors that affect the efficiency of the antenna and make it high or low are the dielectric loss, the conductor loss, the reflected power (Voltage Standing Wave Ratio), the cross polarized loss, and power dissipated in any loads in the element.

$$e = \frac{P_{rad}}{P_{rec}}$$

Where, P_{rad} =Power radiated by the antenna, P_{rec} =power fed to the antenna

Radiated efficiency is a measure of the power radiated through the antenna as an electromagnetic wave to the power fed to the antenna terminals. If an antenna could be made to be a totally ideal electrical component, it would transform all of the power fed to its terminals to a radiating electromagnetic energy that propagates into the surrounding space. This is possible only in theory, and thus in real life some of the power fed to the antenna terminals is always lost. For example, the mismatch between the antenna element and the feeding network causes power losses.

Antenna efficiency is a useful and informative measure of antenna "economic efficiency." With a quick glance, the antenna's capability to use the power fed to the connection pads can be evaluated and the amount of power required from the radio module can be determined in order to achieve a certain performance level. Antenna efficiency does not consider radiation direction and thus is a useful performance metric for measuring the efficiency of mobile devices, which have an omni-directional radiation pattern. In mobile devices, no specific direction of radiation is emphasized. On the other hand, if the antenna is supposed to radiate in a specific direction, (i.e. the antenna is designed to have some directive characteristics in its radiation pattern) then antenna gain is a better performance metric.

2) 2.5.2 *Return Loss:* Return loss is an important parameter when testing an antenna. It is related to impedance matching and the maximum power transfer theory. It is also a measure of the effectiveness of an antenna to deliver power from source to antenna.

The return loss (RL) is defined by the ratio of the incident power of the antenna to the power reflected back from the antenna of the source; the mathematical expression is:

$$R_L = 10\log 10 \frac{\mathrm{pin}}{\mathrm{pref}} (\mathrm{dB})$$



International Journal for Research in Applied Science & Engineering Technology (IJRASET) ISSN: 2321-9653; IC Value: 45.98; SJ Impact Factor: 7.429 Volume 9 Issue VI Jun 2021- Available at www.ijraset.com

Another definition of return loss, from equation (2.9), is the difference in dB between the power sent towards the antenna and the power reflected from it. It is always positive when the antenna is passive and negative when it is active. We can express equation (2.18) in terms of voltage-standing-wave-ratio and impedance as follows [18]:

$$R_{L} = 10 \log_{10} \left| \frac{1}{\rho} \right| (dB) = -20 \log_{10} \rho (dB))$$

$$R_{L} = 10 \log_{10} \left| \frac{VSWR + 1}{VSWR - 1} \right| (dB)$$

$$R_{L} = 20 \log_{10} \log_{10} \frac{1 + Z_{2}}{1 - Z_{2}} (dB)$$

Where, ρ is the complex reflection coefficient at the input of the antenna ,

VSWR-voltage standing wave ratio. Z_1 and Z_2 and are the impedance of the source and the antenna respectively

C. Antenna Bandwidth

The antenna bandwidth is defined as the "range of frequencies with in which the antenna conforms to the specific standard with respect to some characteristics" [19]. The antenna characteristics that are used to determine the bandwidth can be input impedance, radiation pattern, Beam width, polarization, side lobe level or gain. The bandwidth of a broadband antenna can be defined as the ratio of the upper to lower frequencies of acceptable operation.

$$BW_{broad \ band} = \frac{f_H}{f_L}$$

The bandwidth of a narrowband antenna can be defined as the percentage of the frequency difference over the center frequency.

$$BW_{broad band} (\%) = \frac{f_H - f_L}{f_L} * 100$$

Where, f_H = upper frequency, f_L = lower frequency f_c =center frequency

D. Radiation Pattern

The radiation pattern of an antenna is the plot of the far field radiation as a function of spatial coordinates which are elevation angle θ and azimuthal angle φ . It is basically the plot of the radiated power of antenna. An isotropic antenna is the one that radiates equally in all directions. An isotropic antenna is not possible to realize in practice and is useful only for comparison purposes. A more practical type is the directional antenna which radiates more power in some directions and less power in other directions. To make parameter comparison, results found for both micro strip and co-planar are also included in the following tables.

Element	Calculated	Triangula	Results for
	results for	r	Octagonal
	Co-planar	cut(mm)	patch
	patch		antenna
	antenna(mm)		(mm)
Width of patch (W)	30.43	10.8	13.04
Length of patch (L)	22.5	10.8	10.63
Length of ground (Lg)	32	10.8	32
Width of ground (Wg)	46	10.8	46

Table 2.2 Calculated dimensions for Octagonal Patch Co planar Antenna



International Journal for Research in Applied Science & Engineering Technology (IJRASET)

ISSN: 2321-9653; IC Value: 45.98; SJ Impact Factor: 7.429 Volume 9 Issue VI Jun 2021- Available at www.ijraset.com

Element	Calculated	Triangular	Results
	results for	cut height	for
	micro strip	(mm)	Octagonal
	patch		patch
	antenna		antenna
	(mm)		(mm)
Width of patch (W)	46	11	13.04
Length of patch (L)	40	11	10.04
Width of ground (Wg)	46	11	46
Length of ground (Lg)	40	11	40

Observing the above Table 2.2, 2.3, it is noticed that, there are variations in dimensions of antenna. This validates the previously established concepts. Some other important conclusions, based on the simulation results, are also discussed in the next section.



Figure 2.2: Model of Co-planar Patch Antenna in HFSS software



Figure 2.3: Model of micro strip Patch Antenna in HFSS software

III. RESULTS

A. Simulation Results for 3 GHz

During simulation, the conducting grounds and the substrates were assumed to be finite in transverse plane.

The below HFSS result shows return loss in dB verses frequency of octagonal micro strip and co planar patch antennas. At 3 GHz frequency the micro strip and co planar patch antennas exhibit a reflection coefficient of -7.50 dB and -1.05 dB respectively.







The radiation efficiency obtained for micro strip antenna is 24% and that for a co planar patch antenna is 67% i.e.co planar patch more efficient than that of micro strip patch antenna. Figure 3.3 and 3.4 shows the far field radiation pattern for micro strip and co planar patch antennas at a solution frequency of 3 GHz respectively.

Radiation Pattern Results:



Figure 3.3: Radiation Pattern of 3 GHz microstrip patch antenna



Figure 3.4: Radiation Pattern of 3 GHz co planar patch antenna



The following figures show 3-D polar plots for micro strip and co planar patch antennas at 3 GHz.



Figure 3.5: 3-D polar plots for co planar patch antenna at 3 GHz





Figure 3.6: 3-D polar plots for mirostrip patch antenna at 3 GHz

Type of	Frequency	Return	Radiation	Directivity
Antenna	(GHz)	loss	efficiency	(dB)
		(-dB)	(%)	
Co planar	3	1.05	67	3.25
Micro strip	3	7.50	24	3.74

Table 3.1 HFSS Simulation result summary

The HFSS Simulation result summary has shown that, for the same operating frequency and substrate, octagonal co planar patch antennas gives higher radiation efficiency than micro strip patch antenna. This is due to one of the factors that affects radiation efficiency is the effective dielectric constant and the value of effective dielectric constant for a co planar antenna design is lower than micro strip antenna design. When effective dielectric constant of the patch decreases the surface wave excitation will reduce to a large extent, which in turn, leads to a lower radiation loss and less dispersion. Due to this reason co planar antennas have high radiation efficiency.

For operating frequencies 3 GHz, return loss for micro strip patch antennas is found to be lower than co planar patch antennas. It is related to impedance matching and the maximum transfer of power. It also shows the effectiveness of the designed antennas to deliver of power from source to antenna. Even if the same feeding (co planar wave guide) and impedance matching techniques(inset) are applied for both antennas, micro strip patch antennas give lower return loss (higher in the negative) than co planar patch antennas. The VSWR for the two antennas is in between 1 to 2 over the entire frequency band which shows that there is a proper impedance matching.



International Journal for Research in Applied Science & Engineering Technology (IJRASET) ISSN: 2321-9653; IC Value: 45.98; SJ Impact Factor: 7.429 Volume 9 Issue VI Jun 2021- Available at www.ijraset.com

The result summary has also shown that directivity for micro strip patch antennas is higher than that of co planar patch antennas. The reason for the low directivity in case of co planar patch antenna is that, it has patch and ground on the same plane so that the electric field below the patch also form a lobe on the other side of the patch forming a broadside pattern, whereas in case of microstrip patch the fields below the patch are shorted by the lower ground making a single lobe in one direction above the patch forming a unidirectional pattern.

IV. CONCLUSION

Here, a CPW fed octagonal-shaped micro strip and co planar patch antenna are designed with the application of inset fed for impedance matching. The micro strip patch antenna consists of a pair of electrically conducting layers separated by a 1.6 mm dielectric material. Likewise, co planar patch antenna efficiency, return loss, radiation pattern and 3D polar plot are obtained for both micro strip and co planar patch antennas. Full wave HFSS simulation of co planar and micro strip patch antenna models shows that for same operating frequency and same substrate, co planar patch antenna gives wider band width and high radiation efficiency than micro strip patch antenna. On the other side, micro strip patch antennas are more compact (lower profile) than co planar patch antenna has got low directivity than micro strip patch antenna. The reason for the low directivity in case of octagonal co planar patch antenna is that it has patch and ground on the same plane so the electric field below the patch also form a lobe on the other side of the patch forming a broadside pattern. But the directivity of the octagonal co planar patch antennas. Since octagonal patch micro strip antenna is more directional than octagonal co planar patch antennas it provides radiation patterns that are stable across the pass band, and are easy to integrate with other microwave circuits and devices. At same time octagonal patch co planar antenna offers better radiation efficiency.

V. RECOMMENDATIONN FOR FUTURE WORK

Finally, it sincerely recommended that, using conductor backed co planar wave guide (CCPWG) helps to increase the directivity of co planar patch antenna. And for the future it is possible to analyze the performance of the two antennas by using conductor backed coplanar wave guide feeding system. The future work should also address the performance comparison of the two antennas for different patch geometry and multi band applications

REFERENCES

- Nitin Muchhal, Abishek Vishway, "A Compact Double U Slotted Micro Strip Patch Antenna for GSM and Wimax Applications", IJCEA Vol 04, Article F072, June 2013
- Shun Yun Lin, "Multi band Folded Planar Mono pole Antenna for Mobile Handset", IEEE Transactions on Antennas and Propagation, Vol. 52, No. 7, pp. 1790-1794, July 2012
- [3] Hao Chun Tung, Shyh Tirng Fang and Kin Lu Wong, "Printed Dual- Band Mono pole Antenna for 2.4/5.2 GHz WLAN Access Point, Microwave and Optical Technology Letters", Vol. 35, No. 4, pp. 286-288, November 2009.
- [4] Mosallaei H, Sarabandi K "Antenna miniaturization and bandwidth enhancement using a reactive impedance substrate", IEEE Transactions on Antennas and Propagation, Vol. 52, Issue 9, Sept. 2014 pp.2403 2414.
- [5] Jen Yea Jan and Liang Chih Tseng, "Small Planar Mono pole Antenna With a Shorted Parasitic Inverted-L Wire for Wireless Communications in the 2.4, 5.2, and 5.8-GHz Bands", IEEE Transactions on Antennas and Propagation, Vol. 52, No. 7, pp.19031905, July 2009.
- [6] Wen -Chung Liu, Ping-Chi Kao "Compact CPW-fed dual folded-strip monopole antenna for 5.8-GHz RFID application", Microwave and optical technology letters, Vol. 48, Issue 8, May 2012, pp. 1614 – 1615.v.
- [7] Peng Sun, Zhenghe Feng "Compact planar monopole antenna with ground branch for GSM/DCS/PCS/IMT2000 operation", Microwave and optical technology letters, Vol. 48, Issue 4, Feb 2006, pp. 719 – 721.
- [8] Ashish Kumar, Bimal Garg, "Rectangular Microstrip Patch Antenna Loaded With Double Orthogonal Crossed Slits In Ground Plane", International Journal of Advance Technology & Engineering Research.2011.
- [9] Rainee N. Simons, "Coplanar Waveguide Circuits, Components, and Systems", John Wiley & Sons, Inc., Publication, New York. 2010
- [10] S. Baligar, U.K. Revankar and K.V. Acharya, "Broadband two-layer shorted patch antenna with low cross-polarisation", IEE Electronics Letters, Vol.37, No.9, pp.547548, 2001.
- [11] M.A.Matin, A.I.Sayeed, "A Design Rule for Inset-fed Rectangular Microstrip Patch Antenna", WSEAS Trans. on Communication, Issue 1, Vol.9, Jan 2010.
- [12] W. Menzel, M. AI-Tikriti and M.B. Espadas Lopez, "Common aperture, dual frequency printed antenna (900 MHz and 60 GHz)", IEE Electronics Letters, Vol.37, No.17, pp.1059-1060, 2014.
- [13] K.C. Gupta, Inder Bahl and Ramesh Garg, "Microstrip lines and slot lines", Artech House, March 1996.
- [14] Kin-Lu Wong, Chun-Yi Lin, Fa-Shian Chang, "Internal UMTS patch antenna for a sliding mobile phone", Microwave and optical technology letters, Vol. 48, Issue 4, pp. 726 – 729, 2006.

International Journal for Research in Applied Science & Engineering Technology (IJRASET)



ISSN: 2321-9653; IC Value: 45.98; SJ Impact Factor: 7.429 Volume 9 Issue VI Jun 2021- Available at www.ijraset.com

- [15] D. Patel, and F. Raval, "Design and cavity model analysis of inset feed rectangular microstrippatch antenna", Published in IEEE Conference NUiCONE-2012, 06-08 December 2011, India.
- [16] P. Ciais, C. Luxey, A. Diallo, R. Staraj, G. Kossiavas, "Pentaband internal antenna for handset communication devices", Microwave and optical technology letters, Vol. 48, Issue 8, pp. 1509 – 1512, 2007.
- [17] Saou-Wen Su, Kin-Lu Wong, Chia-Lun Tang, and Shih-Huang Yeh, "Wide band Mono pole Antenna Integrated Within the Front-End Module Package", IEEE Transactions on Antennas and Propagation, Vol. 54, No. 6, pp. 1888-189, 2013.
- [18] D.D. Krishna, M. Gopikrishna, C. K. Anandan, P. Mohanan, and K. Vasudevan," CPW-Fed Koch Fractal Slot Antenna for WLAN/WiMAX Applications", IEEE Antennas and wireless propagation letters, Vol.7, pp-389-392, 2008.
- [19] Paul L. Chin, Atef Z. Elsherbeni and Charles E. Smith, "Characteristics of Coplanar Bow-Tie Patch Antennas", IEEE International Symposium on Antennas and Propagation and URSI National Radio Science Meeting, San Antonio, Texas, pp. I 398401, July 2002.
- [20] Zhengwei Du, Ke Gong and Jeffrey Shiang Fu, "A Novel Compact Wide-Band Planar Antenna for Mobile Handsets", IEEE Transactions on Antennas and Propagation, Vol. 54, No. 2, pp. 613-619, 2006.
- [21] Neha Ahuja, Rajesh Khanna, Jaswinder kaur, "Dual Band Defected Ground Microstrip Patch Antenna for WLAN / WiMax and Satellite Application", International Journal of Computer Applications ,Volume 48– No.22, June 2012.
- [22] P. J. Soh, M. K. A. Rahim, A. Asrokin, and M. Z. A. Abdul Aziz, "Comparative RadiationPerformance of Different Feeding Techniques for a Microstrip Patch Antenna", 2005 AsiaPacific Conference on Applied Electromagnetic Proceedings, 2021 December 2005, Johor, Malaysia.
- [23] Amit A. Deshmukh, K. P. Ray, and AmeyaKadam, "Proximity fed Circular Microstrip Antennas", Applied Electromagnetics Conference, (AEMC), 2011, IEEE Conference Proceedings, 18-22 December 2011, Kolkata, India
- [24] D. M. Pozar and D. H. Schaubert, "Microstrip Antennas: The analysis and design of microstrip antennas and arrays", IEEE Press, New York, 1995.
- [25] G. Kumar, K. P. Ray: "Broadband microstrip antennas". Artech House, 2003.
- [26] Bharti Gupta, Sangeeta Nakhate, Madhu Shandilya, "Compact Ultra-Wideband Microstrip Antenna with Modified Ground Plane for Bandwidth Enhancement", International Journal of Computer Applications Volume 49– No.19, July 2012,
- [27] Neha Ahuja, Rajesh Khanna and Jaswinder Kaur, "Design of single band RMPA for WLAN application", IJCA, 2012
- [28] Iulian Rosu, "Microstrip, Stripline, and CPW Design", YO3DAC / VA3IUL
- [29] Cheng P. Wen, IEEE Member, "Coplanar Waveguide: a surface strip transmission line suitable for nonreciprocal gyromagnetic device applications", IEEE Transactions on Microwave Theory And Techniques, VOL. MTT-17, NO.12, December 2011.
- [30] Lorena I. Basilio, Michael A.Khayat, Jeffery Williams, Stuart A.Long, "The Dependence of the Input Impedance on Feed Position of Probe and Microstrip Line - Fed patch Antennas", IEEE Trans. Antennas Propagat, Vol.49, pp.45-47, Jan. 2001
- [31] K. Li, C. H. Cheng, T. Matsui and M. Izutsu, "Coplanar patch antennas: principle, simulation and experiemnt," 2001 IEEE AP-S International Symposium and USNC/URSI National Radio Science Meeting, Vol. 3, no. 73, pp. 402-405, Boston, USA, Jul. 8-13, 2014
- [32] C.A. Balanis, "Antenna Theory", 2nd ed. New York: John Wiley & Sons, Inc., 1997
- [33] Balans, A. Constantine, "Antenna Theory Analysis and Design" 3th Edition. John Wiley & Sons. 20
- [34] Ashish Kumar Sahu, "DESIGN AND ANALYSIS OF POLARIZATION RECONFIGURABLE MICROSTRIP PATCH ANTENNAS", master thesis, India, institute ofRourkela, Odisha, 769008, 2015, pp22-33
- [35] Randy Bancroft, Microstrip and Printed Antenna Design, 2ndedition, Republication, July 2008. 05



VI.AUTHORS BRIEF PROFILES

Dr K. Rameshbabu^{#1} working as a Associate.Professor, in Electronic Communication Technology stream, EET Department,ETU, Ethiopia, He did B.E (ece), M.Tech, PGDST, Ph.D having 22+ years of Experience. He is Guest professor for various colleges affiliated to universities in India. He is member of IEEE, ISTE, VSI.IJCSIT, IRED he is reviewer for many journals & published 36+ papers in international journals and conferences & also conducted, attended many Faculty Development Programmers. His area of interest embedded systems, digital systems, Antenna Design etc.



Mr Mesay.Mengstie^{#2} working as a Dean of EET&ICT,ETU, Addis Ababa, Ethiopia. He holds B.Sc. M.Sc. He is also very good Teacher, Administrator. His area of interest in research is Electronics Communication, especially signal & image processing etc.



Mr Mulushewa.Getachew^{#3} working as a head of EET,ETU, Addis Ababa, Ethiopia. He holds B.Sc. M.Sc. He is also very good Teacher, Administrator. His area of interest in research is Electronics Communication, especially Antenna ,Micro wave Engineering etc.











45.98



IMPACT FACTOR: 7.129







INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Call : 08813907089 🕓 (24*7 Support on Whatsapp)