iJRASET
International Journal For Research in Applied Science and Engineering Technology



INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Volume: 14 **Issue:** XI **Month of publication:** November 2026

DOI: https://doi.org/10.22214/ijraset.2026.85627

www.ijraset.com

Call: 08813907089 | E-mail ID: ijraset@gmail.com

International Journal for Research in Applied Science & Engineering Technology (IJRASET)
ISSN: 2321-9653; IC Value: 45.98; SJ Impact Factor: 7.538
Volume 14 Issue XI Nov 2026- Available at www.ijraset.com

Beyond Qubit Count: A Comparative Review of Quantum Chip Architectures, Error Correction, and the Path to Fault-Tolerant Computing

Mr. Sairaj Dalvi[1], Mr. Suyog Salvi[2], Mr. Tanmay Patil[3], Prof. Mrs. Ravina Khachane[4]
Shivajirao S. Jondhale College of Engineering & Technology, Asangaon, Maharashtra, India

Abstract: ***Quantum processors are often compared by the number of physical qubits they contain. That number, however, does not by itself indicate whether a processor can execute a useful computation reliably. Qubit coherence, gate and measurement fidelity, connectivity, control infrastructure, fabrication yield, and the overhead of quantum error correction all influence practical capability. This paper presents a structured comparative review of six major quantum-computing modalities: superconducting circuits, trapped ions, photonic systems, silicon-spin qubits, neutral atoms, and topological approaches. It examines their physical implementations, operational strengths, engineering constraints, and prospects for scaling. Particular attention is given to surface-code error correction and the 105-qubit Willow processor result reported by Google Quantum AI, which demonstrated below-threshold surface-code memory and a logical-error suppression factor of 2.14 ± 0.02 when code distance increased by two. The paper also considers cryogenic control, wiring, modular interconnects, fabrication variability, real-time decoding, and the Indian National Quantum Mission. The review finds that progress towards fault tolerance is best assessed through logical performance and system-level engineering rather than physical-qubit count alone. No modality currently removes the need to address scaling overhead, reliable operations, and application-level advantage.***

Index Terms: ***Quantum computing; quantum chips; qubit architectures; quantum error correction; surface code; logical qubits; fault-tolerant computing; cryogenic control.***

I. INTRODUCTION

Classical computing has advanced through improvements in semiconductor devices, circuit design, and manufacturing. Quantum computing follows a different model. It uses quantum states to represent and process information, and may offer advantages for selected problems in quantum simulation, chemistry, and some mathematical tasks. Such advantages are problem-dependent; a quantum processor is not a general replacement for a classical computer.

The physical device at the centre of a quantum computer is the quantum processing unit (QPU). A QPU contains qubits, control and readout structures, and connections that allow quantum operations to be performed. The qubit technology chosen determines important system properties, including operating temperature, gate duration, connectivity, fabrication route, and measurement method. DiVincenzo's criteria remain a useful foundation for evaluating physical implementations [1].

A common way of comparing processors is to quote their physical-qubit count. This is an incomplete measure. A processor with many noisy qubits may be less useful than a smaller processor with better fidelity and more effective error correction. The central question is therefore not simply how many qubits can be fabricated, but how reliably those qubits can be controlled, connected, measured, and assembled into logical qubits.

This paper reviews six major hardware modalities and analyses the engineering requirements that connect device-level performance to fault-tolerant computation. It is intended as a comparative review, not as a report of new laboratory measurements or an experimentally validated benchmark.

II. REVIEW SCOPE AND METHODOLOGY

This study uses a focused narrative-review approach. The technical discussion is based on foundational literature on quantum computation, peer-reviewed research on quantum error correction and processor architectures, and official programme information. The supplied background document, “Quantum Chips: Architecture, Technologies and the Road to Fault-Tolerant Computing,” provided the initial topic structure and technology categories.

©IJRASET: All Rights are Reserved

The review compares modalities using the following dimensions: (i) physical carrier of the qubit; (ii) operating environment; (iii) control and measurement approach; (iv) principal strengths; (v) major scaling constraints; and (vi) relevance to fault-tolerant architectures. The Willow discussion is limited to claims reported in the cited Nature paper. National Quantum Mission details are taken from the Government of India's Department of Science and Technology.

No new experiments, simulations, device measurements, or statistical meta-analysis were conducted. Consequently, the paper does not claim original experimental results. Performance figures are attributed to the cited sources and should be interpreted in the context of each source's device, protocol, and measurement definition.

III. QUANTUM COMPUTING FUNDAMENTALS

A classical bit is represented by either 0 or 1. A pure single-qubit state can be expressed as

$$|\psi\rangle = \alpha|0\rangle + \beta|1\rangle, \quad |\alpha|^2 + |\beta|^2 = 1$$

where α and β are complex probability amplitudes. Measurement in the computational basis returns 0 with probability $|\alpha|^2$ and 1 with probability $|\beta|^2$. Superposition does not mean that a qubit simply stores two independently readable classical values; measurement produces a single outcome.

Entanglement describes correlations in a joint quantum state that cannot be represented as independent states of the constituent qubits. Quantum gates transform qubit states. Single-qubit gates manipulate individual states, while two-qubit gates create and control interactions between qubits. Interference is used by algorithms to alter the probabilities of measurement outcomes.

Decoherence occurs when unwanted interactions with the environment degrade quantum information. Energy relaxation and loss of phase coherence are commonly characterised by T1 and T2 measurements, respectively. Gate errors, leakage, readout errors, crosstalk, and correlated events also affect processor performance. The engineering challenge is to perform a sufficiently long sequence of accurate operations before errors overwhelm the computation.

IV. COMPARISON OF QUANTUM CHIP ARCHITECTURES

1) Superconducting circuits: Superconducting qubits are fabricated electrical circuits that use nonlinear circuit elements, commonly Josephson junctions, to create an effective two-level system. Microwave pulses implement gates, and resonators are commonly used for readout. The approach supports fast gate operations and benefits from microfabrication methods. Its principal constraints include millikelvin operation, sensitivity to material defects, wiring density, crosstalk, and the need for high-fidelity two-qubit gates.
2) Trapped ions: Trapped-ion processors encode qubits in internal states of individual ions confined by electromagnetic fields in a vacuum. Laser or microwave fields drive operations, and fluorescence-based methods are commonly used for readout. Ions can exhibit long coherence and high operation fidelity. Gate operations are generally slower than in superconducting systems, while scaling requires control of ion motion, trap zones, transport, and optical or microwave delivery.
3) Photonic systems: Photonic approaches encode information in degrees of freedom of individual photons, such as polarisation, path, or time-bin. Waveguides, interferometers, sources, and detectors form the optical processing system. Photons are attractive for communication because they interact weakly with the environment and can travel through optical networks. Photon loss, source quality, detector efficiency, and the implementation of effective photon-photon interactions remain important challenges.
4) Silicon-spin qubits: Silicon-spin devices encode information in electron or nuclear spin states confined in quantum dots or donor systems. Their small size and potential compatibility with semiconductor manufacturing are attractive for dense integration. However, device-to-device variability, charge noise, precise tuning, uniformity, and large-scale control remain significant engineering challenges.
5) Neutral atoms: Neutral-atom processors use laser-cooled atoms trapped and arranged by optical tweezers or optical lattices. Interactions can be engineered, for example, using highly excited Rydberg states. Reconfigurable arrays and large numbers of atoms are attractive features. Atom loss, laser stability, gate fidelity, measurement, and repeated operation are important constraints.
6) Topological approaches: Topological quantum computing seeks to encode information in non-local degrees of freedom that may be less sensitive to certain local disturbances. Majorana zero modes in hybrid semiconductor-superconductor structures are one proposed route. The potential benefit is intrinsic protection against selected error mechanisms, but the experimental requirements for demonstrating, controlling, and scaling topological qubits remain demanding. Announcements and proposed roadmaps should not be treated as proof of a mature fault-tolerant processor.

©IJRASET: All Rights are Reserved | SJ Impact Factor 7.538 | ISRA Journal Impact Factor 7.894 |

V. COMPARATIVE EVALUATION

Modality	Qubit carrier / platform	Potential strengths	Major engineering constraints
Superconducting	Josephson-junction circuit	Fast gates; lithographic fabrication	Millikelvin cooling; coherence; wiring; crosstalk
Trapped ion	Internal states of trapped ions	High fidelity; long coherence	Gate speed; trap scaling; laser/control complexity
Photonic	Photon modes in optical circuits	Communication; low environmental interaction	Photon loss; sources; detectors; interactions
Silicon spin	Electron or nuclear spin	Small footprint; semiconductor compatibility	Device variability; tuning; control uniformity
Neutral atom	Laser-trapped neutral atoms	Large, reconfigurable arrays	Atom loss; laser stability; gate and readout fidelity
Topological	Proposed Majorana-based states	Potential protection from selected local errors	Experimental validation; control; scalability

Table I summarises qualitative trade-offs. It is not a numerical ranking: the modalities use different operating conditions, gate definitions, connectivity models, and benchmark protocols. A fair quantitative comparison requires matched workloads and clearly specified metrics. A useful evaluation should report at least: physical-qubit count; single- and two-qubit gate fidelity; measurement fidelity; coherence; connectivity; gate duration; leakage and correlated-error rates; logical error per correction cycle; and the resource overhead required for a target logical error rate. These metrics should be reported together rather than reduced to a single headline number.

VI. QUANTUM ERROR CORRECTION AND LOGICAL QUBITS

Quantum error correction protects quantum information by encoding it across multiple physical qubits and repeatedly measuring error syndromes. The syndrome measurements reveal information about errors without directly measuring the encoded logical state. Shor's early error-correction scheme established that quantum information can, in principle, be protected against errors [2].

The surface code is a leading approach for two-dimensional arrays with local interactions. Data qubits store the encoded state, while measurement or ancilla qubits perform stabiliser checks. Code distance is a measure of the code's error-detection and correction capability. Increasing code distance generally requires more physical qubits but can suppress logical errors when the underlying physical error rate is below the relevant threshold [3].

The threshold condition is essential. If physical error rates are above threshold, adding more qubits does not deliver the desired reduction in logical error. Even below threshold, practical fault tolerance requires large-scale repeated operation, low-latency decoding, logical gates, state preparation, measurement, and manageable resource overhead.

A logical qubit is therefore the more meaningful unit for assessing fault-tolerant capability. Physical-qubit count remains important, but it must be interpreted alongside logical error rates and the number of physical resources needed to achieve a specified reliability.

VII. WILLOW AND BELOW-THRESHOLD SURFACE-CODE MEMORY

Google Quantum AI reported below-threshold surface-code memories on its Willow superconducting processors [4]. The study described a distance-5 code on a 72-qubit processor and a distance-7 code on a 105-qubit processor, with real-time decoding integrated into the experiment.

For the larger memory, the reported logical-error suppression factor was $\Lambda = 2.14 \pm 0.02$ when code distance increased by two. The paper reported a distance-7 logical memory with an error per correction cycle of $0.143\% \pm 0.003\%$. It also reported that the logical memory lifetime exceeded that of its best constituent physical qubit by a factor of 2.4 ± 0.3.

These results are significant because they demonstrate a central signature of below-threshold error correction: increasing code distance reduces logical error rather than making the encoded memory less reliable. The work also reported real-time decoding with an average decoder latency of 63 microseconds at distance 5, while the correction-cycle time was 1.1 microseconds.

©IJRASET: All Rights are Reserved | SJ Impact Factor 7.538 | ISRA Journal Impact Factor 7.894 |

The result should nevertheless be interpreted precisely. It demonstrates improved quantum memory, not a complete fault-tolerant computer capable of executing arbitrary large-scale algorithms. The paper itself identifies further challenges in scaling logical operations, software, calibration, decoders, and the overall system. The distinction between a successful logical memory experiment and application-level quantum advantage is important.

VIII. SYSTEM-LEVEL ENGINEERING CHALLENGES

1) Cryogenic operation and thermal load: Superconducting processors require very low operating temperatures. Each control and readout line can contribute thermal load, and the cooling capacity available at the coldest stages is limited. Scaling therefore requires careful thermal design, filtering, attenuation, multiplexing, and potentially cryogenic control electronics.
2) Wiring and control: A growing processor requires many control and measurement channels. Conventional room-temperature electronics connected by individual lines do not scale indefinitely. Multiplexed readout, integrated control, and improved packaging are active engineering directions, but they must not introduce additional noise or unacceptable latency.
3) Fabrication and variability: Defects, interface loss, junction variation, and material contamination can produce qubit-to-qubit differences. Reproducible fabrication and reliable packaging are necessary for improving yield and reducing calibration overhead.
4) Connectivity and modularity: Local connectivity can increase circuit depth when distant qubits must interact. Modular chiplets may help overcome limits on die size and yield, but inter-chip links must preserve quantum information with sufficiently low loss and error.
5) Real-time decoding: Error correction produces syndrome data that must be processed quickly enough to keep pace with the quantum processor. Decoder accuracy, latency, reliability, and integration with control hardware are therefore part of the QPU architecture, not merely software concerns.
6) Benchmarking and reproducibility: Processor comparisons can be misleading when they rely on different benchmarks or selectively reported metrics. Publications should state the workload, calibration conditions, error model, sample size, uncertainty, and whether results are measured or simulated.

IX. APPLICATIONS AND THE QUESTION OF QUANTUM ADVANTAGE

Quantum simulation and chemistry are natural research areas because molecules and materials are quantum systems. Quantum processors may eventually help model selected chemical processes or material properties that are difficult to simulate classically. The scale and accuracy required for practical applications remain substantial.

Cryptography is another important area. A sufficiently large fault-tolerant quantum computer running Shor's algorithm could threaten widely used public-key cryptographic systems. This is one reason governments and standards organisations are preparing post-quantum cryptographic methods that run on conventional computers.

Optimisation and machine learning are frequently discussed as potential application areas. However, a quantum approach should not be assumed to outperform the best classical method. Any claim of quantum advantage should specify the practical task, input size, comparison baseline, accuracy, total runtime, and hardware overhead.

In the near term, hybrid quantum-classical systems are likely to remain important. Classical processors can manage control, optimisation, compilation, and error decoding while quantum processors execute selected quantum operations.

X. INDIA'S NATIONAL QUANTUM MISSION

The Government of India approved the National Quantum Mission (NQM) on 19 April 2023 with an outlay of ₹6,003.65 crore for the period 2023–24 to 2030–31 [5]. The mission aims to support scientific and industrial research and develop an ecosystem for quantum technologies and applications.

The stated computing objective includes developing intermediate-scale quantum computers with 50–1,000 physical qubits over an eight-year period, across platforms including superconducting and photonic technologies. The mission also covers quantum communication, sensing, metrology, and supporting components.

For India's research ecosystem, progress will depend on more than processor announcements. Access to specialised fabrication, cryogenic systems, lasers, photonic components, low-noise electronics, test facilities, and trained researchers will be important. Collaboration among universities, national laboratories, startups, and industry can help build this capability.

©IJRASET: All Rights are Reserved | SJ Impact Factor 7.538 | ISRA Journal Impact Factor 7.894 |

XI. RESEARCH GAPS AND FUTURE DIRECTIONS

The review identifies several priorities for future research. First, benchmark reporting should move beyond physical qubit counts and provide comparable logical metrics. Second, researchers should quantify the full resource overhead of logical operations, including state preparation, measurement, routing, decoding, and interconnects. Third, system-level co-design is needed so that qubits, control electronics, cryogenics, packaging, and classical processing are developed together.

A further need is reproducible comparison across modalities. Different platforms should be evaluated using application-relevant workloads and transparent assumptions. Claims based on vendor roadmaps or proposed future capabilities should be clearly separated from peer-reviewed experimental demonstrations.

Finally, practical quantum advantage should be established through end-to-end studies that include input preparation, quantum execution, error mitigation or correction, classical post-processing, and comparison with strong classical baselines.

XII. CONCLUSION

This review compared superconducting, trapped-ion, photonic, silicon-spin, neutral-atom, and topological approaches to quantum chip development. Each modality offers a different balance of gate speed, coherence, connectivity, fabrication compatibility, operating environment, and scaling difficulty. No single architecture can currently be identified as the universal solution for fault-tolerant quantum computing.

The Willow surface-code experiment is an important demonstration of below-threshold logical memory and shows why logical performance is a more informative measure than physical-qubit count alone. It does not, however, remove the remaining challenges in logical operations, decoding, wiring, cooling, fabrication, modular interconnects, and application validation.

The path to practical quantum computing will require coordinated progress across quantum devices, materials, control electronics, classical computing, and error-correction methods. For India, the National Quantum Mission provides a policy framework for building research capacity and domestic capability. Ultimately, the success of quantum chips should be judged by reliable, reproducible, and useful computation rather than by qubit counts or roadmap targets alone.

REFERENCES

[1] D. P. DiVincenzo, “The physical implementation of quantum computation,” Fortschritte der Physik, vol. 48, no. 9–11, pp. 771–783, 2000, doi: 10.1002/1521-3978(200009)48:9/11<771::AID-PROP771>3.0.CO;2-E.

[2] P. W. Shor, “Scheme for reducing decoherence in quantum computer memory,” Physical Review A, vol. 52, no. 4, pp. R2493–R2496, 1995, doi: 10.1103/PhysRevA.52.R2493.

[3] A. G. Fowler, M. Mariantoni, J. M. Martinis, and A. N. Cleland, “Surface codes: Towards practical large-scale quantum computation,” Physical Review A, vol. 86, 032324, 2012, doi: 10.1103/PhysRevA.86.032324.

[4] Google Quantum AI and Collaborators, “Quantum error correction below the surface code threshold,” Nature, vol. 638, pp. 920–926, 2025, doi: 10.1038/s41586-024-08449-y.

[5] Department of Science and Technology, Government of India, “National Quantum Mission,” 2023. [Online]. Available: https://dst.gov.in/national-quantum-mission-nqm. Accessed: Nov. 6, 2026.

[6] R. P. Feynman, “Simulating physics with computers,” International Journal of Theoretical Physics, vol. 21, pp. 467–488, 1982, doi: 10.1007/BF02650179.

[7] P. W. Shor, “Algorithms for quantum computation: Discrete logarithms and factoring,” in Proc. 35th Annual Symposium on Foundations of Computer Science, 1994, pp. 124–134, doi: 10.1109/SFCS.1994.365700.


[8] L. K. Grover, “A fast quantum mechanical algorithm for database search,” in Proc. 28th Annual ACM Symposium on Theory of Computing, 1996, pp. 212–219, doi: 10.1145/237814.237866.

[9] Google Quantum AI and Collaborators, “Learning high-accuracy error decoding for quantum processors,” Nature, vol. 635, pp. 834–840, 2024, doi: 10.1038/s41586-024-08148-8.

[10] National Quantum Mission, “Cabinet approves National Quantum Mission to scale-up scientific & industrial R&D for quantum technologies,” Press Information Bureau, Government of India, Apr. 19, 2023. [Online]. Available: https://www.pib.gov.in/Pressreleaseshare.aspx?PRID=1917888.

AUTHOR DECLARATION

The authors should review this manuscript, verify all technical statements and references, and confirm that the final submitted version reflects their own understanding and contribution. This manuscript is a literature-based review and does not report new experimental measurements.



10.22214/IJRASET

45.98

IMPACT FACTOR: 7.129

IMPACT FACTOR: 7.429

INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Call : 08813907089 (24*7 Support on Whatsapp)