



IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Volume: 3 Issue: V Month of publication: May 2015 DOI:

www.ijraset.com

Call: 🛇 08813907089 🕴 E-mail ID: ijraset@gmail.com

International Journal for Research in Applied Science & Engineering Technology (IJRASET)

Synthesis of Planar Mechanisms; Part IV: Four-bar Mechanism for Four Coupler Positions Generation

Galal Ali Hassaan

Emeritus Professor, Department of Mechanical Design & Production, Faculty of Engineering, Cairo University, Egypt

Abstract— The objective of the paper is to propose an approach relying on forming a mathematical model for a planar fourbar mechanism position incorporating four coupler positions. The model consists of 10 nonlinear equations considering the transmission angle of the mechanism in the four coupler positions. The equations are solved using the command 'fsolve' of MATLAB. A case study is presented as a justification for the proposed approach. Exact coupler positions are attained with transmission angles not more than 18.5 % of the optimum value of 90 degrees.

Keywords— Planar mechanisms synthesis, four-bar mechanisms, four-coupler position generation, nonlinear kinematic equations, computer-aided mechanism synthesis

I. INTRODUCTION

Mechanism synthesis techniques range from simple graphical techniques going through analytical approaches with many assumptions and trials to sophisticated techniques using optimization application.

The subject of mechanism synthesis has occupied the attention of researchers over decades. Only some publications are reviewed over the last one and half decades to highlight some of the efforts focused on mechanism synthesis.

Russel (2001) presented several methods for synthesizing adjustable spatial mechanisms. He synthesized spatial 4 and 5-bar mechanisms for different phases of prescribed rigid body positions. He extended his approach to incorporate rigid body tolerance problems [1]. Cabrera, Simon and Prado (2002) used a searching procedure applying genetic algorithms to the problem of synthesis of 4-bar planar mechanisms. They outlined the possibility of extending their method to other mechanisms [2]. Smaili and Zeineddine (2003) presented a software package based on Simulink and Matlab for the synthesis and analysis of linkage mechanisms. They coded precision point synthesis methods and optimization synthesis techniques to yield a mechanism for a specific task [3].

Bultovic and Djordjevic (2004) studied the optimal synthesis of a 4-bar linkage by method of controlled deviation. They used the Hooke-Jeeves optimization technique without dependence on the initial selection of the projected variables [4]. Shiakolas, Koladiya and Kebrle (2005) presented a methodology combining different evolution, an evolutionary optimization and geometric control of precision positions for mechanism synthesis. They employed two penalty functions, one for constraint violation and one for relative accuracy [5]. Damangir, Jafarijashemi, Mamduhi and Zohoor (2006) proposed a curvature path description method for path generation of planar mechanisms. The objective function was independent of rotation and translation transformations [6]. Xi and Chen (2007) proposed an approach for the kinematic synthesis of a crank-rocker mechanism to generate a coupler motion passing through a prescribed set of positions [7]. Schrocker, Juttler and Agner (2008) presented an evolution based method for optimal mechanism synthesis. They used curve and surface evolution techniques from computer-aided design and image processing [8].

Al-Smadi (2009) calculated the mechanism parameters required to achieve a set of prescribed rigid body positions [9]. Peng (2010) developed an optimal synthesis method based on link length structural error for the kinematic synthesis of adjustable planar mechanisms. He developed the optimal synthesis method for adjustable planar 4-bar mechanisms for three typical synthesis tasks [10]. Mutawe, Al-Smadi and Sodhi (2011) discussed the path generation of 4-bar mechanism with position tolerance variations due to joint running tolerance [11]. Hwang and Wang (2012) presented a synthesis technique for the planar Watt-I six-bar mechanism with a coupler point passing through 3 or 4 acceleration poles. They provided examples to illustrate the feasibility of their proposed method [12].

Larochelle (2013) presented a dimensional synthesis technique for solving the mixed exact and approximate motion synthesis problem for planar RR kinematic chains. His algorithm did not require the use of any optimization algorithm [13]. Kamat, Hoshing, Pawar, Lokhande, Patankar and Hatawalane (2014) synthesized an adjustable planar 4-bar mechanism for different angles. They adjusted the length of different links to obtain different paths accurately [14]. Shete and Kulkarni (2015) used genetic algorithm to achieve a desired trajectory. They analyzed three problems having different curvature [15].

II. NOMENCLATURE

 f_1, f_2, \dots, f_{10} :

nonlinear mechanism functions.

International Journal for Research in Applied Science & Engineering

Technology (IJRASET)

r ₁ , r ₂ , r ₃ , r ₄ :	lengths of links 1, 2, 3 and 4.
r_{1n}, r_{3n}, r_{4n} :	normalized lengths of links 1, 3 and 4.
x_{A1}, y_{A1} :	coordinates of point A ₁ .
x _{A2} ,y _{A2} :	coordinates of point A_2 .
x ₁ , x ₂ ,, x ₁₀ :	mechanism unknown parameters.
$\mu_1, \mu_2, \mu_3, \mu_4$:	mechanism transmission angles in the four coupler positions.
θ_1 :	orientation of link 1 (frame).
$\theta_{21}, \theta_{31}, \theta_{41}$:	orientation of links 2, 3 and 4 in the first mechanism position.
$\theta_{22}, \theta_{32}, \theta_{42}$:	orientation of links 2, 3 and 4 in the second mechanism position.
$\theta_{23}, \theta_{33}, \theta_{43}$:	orientation of links 2, 3 and 4 in the third mechanism position.
$\theta_{24}, \theta_{34}, \theta_{44}$:	orientation of links 2, 3 and 4 in the fourth mechanism position.

III.METHODOLOGY

The proposed methodology is applied to standard 4-bar mechanisms having fixed lengths. The approach is applied as follows:

The desired 4 positions of the coupler are assigned in the motion plane.

Closed loops are formed for the mechanism in the 4 positions.

2 equations are written for each loop in the x and y directions.

4 equations are written for the 4 transmission angles (one per mechanism position).

The 10 equations are written in a normalized form by dividing each link dimension by r₂.

The equations are written such that the right hand side is zero.

The model in its final form consists of 6 nonlinear equations in 6 unknowns.

The model is solved using MATLAB for the mechanism unknowns.

A. Requirements

It is desired to have a coupler of a known length in 4 positions: A_1B_1 , A_2B_2 , A_3B_3 and A_4B_4 with known orientations θ_{31} , θ_{32} , θ_{33} and θ_{34} (Fig.1).



Fig.1 Desired coupler 4 positions

B. Mechanism

Fig.2 shows a 4-bar mechanism in 4 positions corresponding to the desired 4 coupler positions.





4 polygons are closed which are required for displacement analysis in each mechanism position.

C. Analysis

Volume 3 Issue V, May 2015 ISSN: 2321-9653

International Journal for Research in Applied Science & Engineering Technology (IJRASET)

The 4 coupler positions are: A_1B_1 , A_2B_2 , A_3B_3 and A_4B_4 .	
Polygon 1: OA_1B_1QO . The displacement equation across the polygon is:	
$\underline{\mathbf{r}}_1 + \underline{\mathbf{r}}_{21} + \underline{\mathbf{r}}_{31} + \underline{\mathbf{r}}_{41} = 0$	
Working with the vectors components in the x-direction ; $\sum r_x = 0$ gives:	
$r_1 \cos\theta_1 + r_2 \cos\theta_{21} + r_3 \cos\theta_{31} + r_4 \cos\theta_{41} = 0$	(1)
Working with the vectors components in the y-direction ; $\sum r_y = 0$ gives:	
$r_1 \sin \theta_1 + r_2 \sin \theta_{21} + r_3 \sin \theta_{31} + r_4 \sin \theta_{41} = 0$	(2)
Polygon 2: OA ₂ B ₂ QO. The displacement equation across the polygon is:	
$\underline{\mathbf{r}}_1 + \underline{\mathbf{r}}_{22} + \underline{\mathbf{r}}_{32} + \underline{\mathbf{r}}_{42} = 0$	
Working with the vectors components in the x-direction ; $\sum r_x = 0$ gives:	
$r_1 cos\theta_1 + r_2 cos\theta_{22} + r_3 cos\theta_{32} + r_4 cos\theta_{42} = 0$	(3)
Working with the vectors components in the y-direction ; $\sum r_y = 0$ gives:	
$r_1 \sin\theta_1 + r_2 \sin\theta_{22} + r_3 \sin\theta_{32} + r_4 \sin\theta_{42} = 0$	(4)
Polygon 3: OA ₃ B ₃ QO. The displacement equation across the polygon is:	
$\underline{\mathbf{r}}_1 + \underline{\mathbf{r}}_{23} + \underline{\mathbf{r}}_{33} + \underline{\mathbf{r}}_{43} = 0$	
Working with the vectors components in the x-direction ; $\sum r_x = 0$ gives:	
$r_{1}\cos\theta_{1} + r_{2}\cos\theta_{23} + r_{3}\cos\theta_{33} + r_{4}\cos\theta_{43} = 0$	(5)
Working with the vectors components in the y-direction ; $\sum r_y = 0$ gives:	
$r_1 \sin \theta_1 + r_2 \sin \theta_{23} + r_3 \sin \theta_{33} + r_4 \sin \theta_{43} = 0$	(6)
Polygon 4: OA_4B_4QO . The displacement equation across the polygon is:	
$r_1 + r_{24} + r_{34} + r_{44} = 0$	
Working with the vectors components in the x-direction ; $\sum r_x = 0$ gives:	
$r_1 \cos\theta_1 + r_2 \cos\theta_{24} + r_3 \cos\theta_{34} + r_4 \cos\theta_{44} = 0$	(7)
Working with the vectors components in the y-direction ; $\sum r_y = 0$ gives:	
$r_1 \sin \theta_1 + r_2 \sin \theta_{24} + r_3 \sin \theta_{34} + r_4 \sin \theta_{44} = 0$	(8)
Unknowns in Eqs. 33-40: $r_1, r_2, r_4, \theta_1, \theta_{21}, \theta_{41}, \theta_{22}, \theta_{42}, \theta_{23}, \theta_{43}, \theta_{24}$ and θ_{44} .	
Number of unknowns: 12.	
Number of equations so far: 8	
The number of design parameters is reduced through:	
1. Assigning the ground length, r_1 .	
2. Using normalized dimensions by referring all the dimensions to r_{2} .	
In this case, the unknown design parameters are: $x_1 = r_{42}$, $x_2 = \theta_1$, $x_4 = \theta_{41}$, $x_5 = \theta_{22}$.	$x_6 = \theta_{42}$, $x_7 = \theta_{22}$, x_8
$= \theta_{42}, x_0 = \theta_{24} \text{ and } x_{10} = \theta_{44}.$	-0 •42,, •23,0
Number of unknowns is reduced to 10.	
Two more equations may be written for the transmission angle in 4 positions of the mechanism.	
The transmission angle is related to links 3 and 4 orientation angles through:	
$\mu_1 = -\theta_{41} - \pi - \theta_{21}$	
$\mu_1 = \theta_{42} - \pi - \theta_{22}$	
$\mu_2 = \theta_{42} - \pi - \theta_{32}$	
$\mu_{3} = \theta_{43} - \pi - \theta_{24}$	
Now the kinematical model equations are written in the normalized form as:	
$f_{t} = r_{t} \cos x_{0} + \cos x_{0} + r_{0} \cos \theta_{0} + x_{0} \cos x_{0}$	(9)
$f_1 = r_1 \sin x_2 + \sin x_2 + r_2 \sin \theta_{31} + x_1 \cos x_4$ $f_2 = r_1 \sin x_2 + \sin x_2 + r_2 \sin \theta_{31} + x_1 \sin x_4$	(10)
$f_2 = r_1 \cos x_2 + \cos x_3 + r_3 \cos \theta_{22} + x_1 \sin x_4$	(10) (11)
$f_1 = r_1 \sin x_2 + \sin x_2 + r_2 \sin \theta_{22} + x_1 \cos x_6$	(11)
$f_{z} = r_{10} \sin x_{2} + \cos x_{3} + r_{30} \sin x_{32} + x_{10} \sin x_{6}$	(12)
$\mathbf{f}_{2} = \mathbf{r}_{10} \cos x_{2} + \cos x_{1} + \mathbf{r}_{30} \cos \sigma_{32} + \mathbf{x}_{10} \cos \sigma_{32}$ $\mathbf{f}_{4} = \mathbf{r}_{5} \sin x_{5} + \sin x_{5} + \mathbf{r}_{5} \sin \theta_{50} + \mathbf{x}_{5} \sin x_{5}$	(13)
$f_0 = r_1 \cos \alpha_2 + \cos \alpha_1 + r_2 \cos \theta_{\alpha_1} + x_1 \cos \alpha_2$	(15)
$\mathbf{f}_{1} = \mathbf{r}_{10} \cos x_{2} + \cos x_{3} + \mathbf{r}_{30} \cos \sigma_{34} + \mathbf{A}_{10} \cos x_{10}$ $\mathbf{f}_{2} = \mathbf{r}_{10} \sin x_{2} + \sin x_{2} + \mathbf{r}_{20} \sin x_{10}$	(15)
$f_{0} = (T\Delta_{1} - x_{1} + \pi + \theta_{2})^{2} + (T\Delta_{0} - x_{1} + \pi + \theta_{2})^{2}$	(17)
$10 - (111) - A_1 + h + V_3 J + (111) - A_6 + h + V_3 J$	(1/)

 $f_{10} = (TA_3 - x_8 + \pi + \theta_{33})^2 + (TA_4 - x_{10} + \pi + \theta_{34})^2$ (18)

Equations 17 and 18 are functions of the 4 transmission angles of the 4-bar mechanism in its 4 positions corresponding to each coupler position. It's a novel use of those relations in such formulation.

www.ijraset.com IC Value: 13.98

International Journal for Research in Applied Science & Engineering Technology (IJRASET)

D. Mechanism Synthesis:

The synthesis equations are equations 9-18 (10 equations).

The equations are nonlinear in 10 unknowns.

The 10 equations are in the form: f = 0

The 10 equations may be solved with MATLAB using its command "fsolve" or any other numerical technique [16].

E. Case Study

It is required to design a 4-bar planar mechanism to move the coupler AB from position A_1B_1 to A_2B_2 to A_3B_3 to A_4B_4 as shown in Fig.3.



$r_3 = AB = 200 \text{ mm}$,	$\theta_{31} = 20^{\circ}$,	$\theta_{32} = 25^{\circ}$,
$\theta_{33} = 30^{\circ}$, $\theta_{34} = 43^{\circ}$			
$x_{B1} = 500$, $y_{B1} = 400$	mm		

Fig.3 Desired coupler 4 positions with location of x_{B1} , y_{B1} .

F. Mechanism Synthesis

A MATLAB code is written to solve Eqs.9-18 satisfying the right hand side which is zero for the 10 equations.

Code inputs:
$$r_{3n} = 5$$
 , $r_{1n} = 6$, $\theta_{31} = 20^{\circ}$, $\theta_{32} = 25^{\circ}$

, $\theta_{33}=30^{\circ}$ and $\theta_{34}=43^{\circ}$

$$TA_1 = TA_2 = TA_3 = TA_4 = 90^{\circ}$$

- (code outpu	it:				
3.7011	(r ₄	n)				
-3.2306	(θ ₁)				
-4.3871	(θ ₂	21)				
5.1740	(θ4	u)				
-3.3370	(θ ₂	22)				
5.4147	(θ4	₁₂)				
0.6475	(θ ₂	23)				
4.9453	(θ4	₁₃)				
-1.5848	(θ ₂	24)				
5.3833	(θ4	₁₄)				
Normalized	d model fi	unctions a	t converg	ence:		
0.0509	-0.1228	-0.0348	0.0155	0.0056	0.0353	-0.0324
0.0447	0.0834	0.0909				
Mechanisn	n dimensi	ons:				

Coupler	length:	\mathbf{r}_3	= 200 mm	
Crank le	ength:	r_2	$=r_{3}\!/r_{3n}=200\!/5=$	40 mm
Rocker	length:	r_4	$= r_{4n} x r_2 = 148.04$	mm

International Journal for Research in Applied Science & Engineering

Technol	logy	(IJRA	SET)

Ground length:	$r_1 = r_{1n}xr_2 = 240$	mm
Ground angle:	$\theta_1 = 174.9^{\circ}$	
Crank orientation:	$\theta_{21} = 108.6^{\circ}$	
	$\theta_{22}=168.8^{\rm o}$	
	$\theta_{23} = 37.1^{\circ}$	
	$\theta_{24}=269.2^{\rm o}$	
Rocker orientation:	$\theta_{41}=296.4^{\rm o}$	
	$\theta_{42} = 310.2^{\circ}$	
	$\theta_{43} = 283.3^{\circ}$	
	$\theta_{44}=308.4^{\rm o}$	

The designed mechanism in its 4 positions is shown in Fig.4.



Transmission angles of the synthesized mechanism:

In the first position:	$\mu_1 = 96.4^{\circ}$.
In the second position:	$\mu_2 = 105.2^{\circ}$.
In the third position:	$\mu_3 = 73.3^{\circ}$.
In the third position:	$\mu_4 = 85.4^{\circ}$.

@ Mechanism type:

www.ijraset.com IC Value: 13.98

 $\begin{array}{lll} L_{min}=&40&mm~(crank)\\ L_{max}=&240&mm\\ L_a=&148\,mm\\ L_b=&200\,mm\\ L_{min}+L_{max}=&280\,mm\\ L_a+L_b&=&348\,mm\\ Then:&L_{min}+L_{max}< L_a+L_b~~and~the~crank~is~the~minimum. \end{array}$

Therefore, the designed mechanism is a crank-rocker Grashof mechanism [17].

IV.CONCLUSIONS

The proposed approach is very accurate and reliable in synthesizing 4-bar planar mechanisms for 4 specific positions of its coupler.

The assumptions are only one dimension (r_1) giving easy and straight forward synthesis of the 4-bar mechanism. The coupler traced exactly the desired 4-positions.

The deviation of the transmission angle of the mechanism from the ideal value of 90° is:

7.1 % error in the first coupler position.

www.ijraset.com IC Value: 13.98 *Volume 3 Issue V, May 2015 ISSN: 2321-9653*

International Journal for Research in Applied Science & Engineering

Technology (IJRASET)

16.9 % error in the second coupler position.

-18.5 % error in the third coupler position.

-5% error in the fourth coupler position.

The transmission angle in all the 4 mechanism positions is within the recommended range of $45^{\circ} \le \mu \le 135^{\circ}$ [18].

REFERENCES

[1] K. Russel, "Kinematic synthesis of adjustable spatial four and five bar mechanisms for finite and multiple separated positions", Ph.D. Thesis, Faculty of New Jersey Institute of Technology, USA, 2001.

[2] J. Cabrera, A. Simon and M. Prado, "Optimal synthesis of mechanisms with genetic algorithms", Mechanism and Machine Theory, vol.37, pp.1165-1177, 2002.

[3] A. Smaili and F. Zeineddine, "A Matlab/Simulink based code for the analysis, synthesis, optimization and simulation of mechanisms", Proceedings of the 2003 American Society for Engineering Education Annual Conference and Exposition, Session 2666, 2003.

[4] R. Bultovic and S. Djordjevic, "Optimal synthesis of a four-bar linkage by method of controlled deviation", Theory and Applied Mechanics, vol.31, issue 3-4, 265-280, 2004.

[5] P. Shiakolos, D. Koladiya and J. Kelorle, "On the optimum synthesis of six bar linkages using differential evolution and the geometric centroid of precision positions technique", Mechanism and Machine Theory, vol.40, pp.319-335, 2005.

[6] S. Damangir, G. Jafarijashemi, M. Mamduhi and H. Zohoor, "Optimum synthesis of mechanisms for path generation using a new curvature based-deflection based objective function", Proceedings of the 6th WSEAS International Conference on Simulation, Modeling and Optimization, Lisbon, Portugal, September 22-24, pp.672-676, 2006.

[7] J. Xie and Y. Chen, "Application back-propagation neural network to synthesis of whole cycle motion generation mechanism", 12th IFToMM World Congress, Besancon, France, June 18-21, 2007.

[8] Schrocker H., Juttler B. and Agner M., "Evolving four-bars for optimal synthesis", Industrial Geometry, FSP Report No.67, April, 2008.

[9] Y. Al-Smadi, "Kinematic synthesis of planar four bar and geared five bar mechanisms with structural constraints", Ph. D. Thesis, Faculty of New Jersey Institute of Technology, USA, 2009.

[10] C. Peng, "Optimal synthesis of planar adjustable mechanisms", Ph. D. Thesis, Faculty of New Jersey Institute of Technology, USA, January, 2010.
[11] S. Mutawe, Y. Al-Smadi and R. Sodhi, "Planar four-bar path generation considering worst case point tolerances", Proceedings of the World Congress on Engineering and Computer Science, 1, October 19-21, San Francisco, USA, 2011.

[12] W. Hwang and J. Wang, "Synthesis of Watt-I path generators with coupler points passing through three or four acceleration poles", Transactions of the Canadian Society for Mechanical Engineering, vol.36, issue 2, pp.149-160, 2012.

[13] P. Larochelle, "Synthesis of planar mechanisms for pick and place tasks with guiding locations", Proceedings of the ASME International Design

Engineering Technical Conferences and Computers and Information in Engineering Conference, August 4-7, Portland, Oregon, USA, 2013.

[14] G. Kamat, G. Hoshing, A. Pawer, A. Lokhande. P. Patankar and S. Hatowalane, "Synthesis and analysis of adjustable planar four-bar mechanism", International Journal of Advanced Mechanical Engineering, vol.4, issue 3, pp.263-268, 2014.

[15] S. Shete and S. Kulkarni, "Dimensional synthesis of four bar mechanism using genetic algorithm", International Journal of Engineering Research, vol.4, issue 3, pp.123-126, 2015.

[16] C. Lopez., "MATLAB programming for numerical analysis", Springer International Publishing, 2014.

[17] R. Norton, "Design of machinery", McGraw-Hill, 2011.

[18] C. Wilson, E. Sadler and J. Peter, "Kinematic and dynamic analysis of machinery", Prentice Hall, 2003

BIOGRAPHY

Galal Ali Hassaan

- A. Emeritus Professor of System Dynamics and Automatic Control.
- B. Has got his B.Sc. and M.Sc. from Cairo University in 1970 and 1974.
- C. Has got his Ph.D. in 1979 from Bradford University, UK under the supervision of Late Prof. John Parnaby.
- D. Now with the Faculty of Engineering, Cairo University, EGYPT.
- E. Research on Automatic Control, Mechanical Vibrations, Mechanism Synthesis and History of Mechanical Engineering.
- F. Published 10's of research papers in international journals and conferences.
- G. Author of books on Experimental Systems Control, Experimental Vibrations and Evolution of Mechanical Engineering.
- H. Editor-in-Chief of IJCT.
- I. Reviewer of some international engineering and technological journals.













45.98



IMPACT FACTOR: 7.129







INTERNATIONAL JOURNAL FOR RESEARCH

IN APPLIED SCIENCE & ENGINEERING TECHNOLOGY

Call : 08813907089 🕓 (24*7 Support on Whatsapp)